



KINGDOM ELECTRONICS CC

Electronic Design and Manufacture
Security & Access Control Equipment

PO Box 1940 • HONEYDEW • 2040
Tel: (011) 791 1362/3749 • Fax: (011) 791 6610

CK 1991 /002586 / 23 VAT Reg No. 4130137047

E-mail: ke-sa@mweb.co.za Website: www.kesa.co.za

TECHNICAL PRODUCT BULLETIN

LCD Timer

Application

- ▶ To automatically turn 12v DC equipment on and off.

Specifications

- ▶ 12v operation, real time clock.
- ▶ Potential free relay contacts.
- ▶ Low standby current 3mA.
- ▶ Current rating 15A@ 12 VDC.
- ▶ 7 day timer, 17 program settings.
- ▶ Supplied in DIN rail plastic housing.
- ▶ Physical size: 80mm x 49mm x 35mm.

Wiring Diagram

- 1 = +12v DC
- 2 = -12v DC

- 3 = N.C.
- 4 = COM
- 5 = N.O.



Installation

- ▶ Connect 12v DC and relay contact to power the equipment.
- ▶ Allow the internal battery to charge to usable level, press the reset switch with a pencil.
- ▶ Set Current Date and Time.
- ▶ Setup programs for turning on and off the equipment.
- ▶ Manual button will override preset programs.